

New

## Dynamic Indication, Greater Control



Multi-color Model



Mono-color Model (Red)

### Compact and Efficient

- Touch sensor enables real-time status confirmations.
- Features simultaneous use of continuous, flashing, and audible alarm conditions.
- Newly developed reflector emits evenly distributed light, preventing ambiguous indication
- High protection rating for operation in harsh environments




## Identify and Resolve Issues Quickly



Notify when tasks are completed



Call for manager or parts




Signal equipment statuses



### Built-in capacitive touch sensor.

- Up to 7 selectable colors
- Able to choose between 4 patterns (red, blue, white, or off) when engaging touch sensor
- Touch sensor is able to detect bare or gloved hands and even when wet
- Ability to choose 2 touch settings: light on only while sensor is being touched, or touch to activate/deactivate continuous light
- Buzzer can be sounded in combination with continuous/flashing light and touch sensor



The Red, Green and Blue wires achieve 7 colors

### Specifications

Model	NE-24A-□ □ : R/Y/G/B/C	NE-M1ANN-M	NE-M1ANB-M	NE-M1ATB-M
Dimensions	Φ56mm			
Operating Voltages	24V DC	12-24V DC		
Mounting location	Indoor			
mounting direction	all directions			
Protection Rating	IP65 NEMA TYPE 4X, 13	IP67 NEMA TYPE 4X, 13	IP65 / NEMA TYPE 4X, 13	
Light Color	Red / Amber / Green / Blue / White	Multi-color ( Red Amber Green Blue White Cyan Purple )		
Sound Pressure	-		88dB Intermittent or Continuous	
Operation Specification	Continuous	Continuous / Flashing		Continuous / Touch sensor
Wiring	Screwless terminal block	Cabtire cable (2m)		

### Options

#### Upper Bracket NE-001D



#### Wall Mount Bracket NE-002D



#### 1/2" NPT Bracket SZP-092D



### Model Code

Monochromatic model **NE-24A-□**

Operating Voltages  
24 : 24V DC

Light color  
R : Red Y : Amber  
G : Green B : Blue  
C : Clear

Multi-color model **NE-M1ATB-M**  
**NE-M1ANB-M**  
**NE-M1ANN-M**

Operating Voltages  
M1 : 12~24V DC

Touch sensor  
T : With Touch Sensor  
N : No Touch Sensor

Light color  
M : Multi-color

Buzzer  
B : With Buzzer  
N : No Buzzer

Multi-color model also available with



learn more on [www.patlite.com](http://www.patlite.com)

\*Download the instruction manual from our website ([www.patlite.com](http://www.patlite.com)) for additional details on wiring and dimensions.

**sensorMATIC**  
SPECIALIST&SOLUTIONS

Sensormatic srl - Via della Beverara 13 - 40131 Bologna - Italia  
Tel. +39 051 6353 511 - Fax +39 051 6345 925 - [www.sensormatic.it](http://www.sensormatic.it)

**PATLITE®**